

PIR MOTION SENSOR BASED LIGHT CONTROL

(Product Code : NS-PIR Sensor)

 NavKar



Infrared Motion Sensor Ceiling Mount

Infrared Motion Sensor Ceiling Mount

High Quality Branded Products Only

Call us on +91-999-663-5607 / +91-941-613-5607

High Quality Branded Infrared Motion Sensor Ceiling Mount

Easy Installation

No Expert Required

High Quality & Reliable

This Kit Includes:-

Infrared Motion Sensor Ceiling Mount

User Manual

Function

- Can identify day and night: The consumer can adjust work ambient light. It can work in the daytime and at night when it is adjusted on the "sun" position (max). It can work in the ambient light less than 3LUX when it is adjusted on the "moon" position (min). As for the adjustment pattern, please refer to

the testing pattern.

- Time-Delay is added continually: When it receives the second induction signals after the first induction, it will compute time once more on the basis of the first time-delay rest.
- Time-Delay is adjustable. It can be set according to the consumer's desire. The minimum time is $10\text{sec} \pm 3\text{sec}$ (preferable time 60sec). The maximum is $7\text{min} \pm 2\text{min}$.

Specification:

Power 50-60W
Frequency 50/60 Hz
Working Temperature -20°C to $+40^{\circ}\text{C}$
Ambient Temperature $3-20^{\circ}\text{C}$
LUX (adjustable)
Time Delay 10sec to 7min
Installation Height 2.2m to 4m
Rated Load 1200W
Load Capacity 300W
Savings 45%
Power Factor $\cos\phi > 0.9$
Detection Distance 0.6m to 1.5m
Motion Speed max 6m/s
Detection Angle $< 24^{\circ}$

nce C)
Dete 360°
ction
Rang
e
Work <93
ing H %
umidi RH
ty
Powe 220-
r Sou 240
rce V/AC
110-
130
V/AC